


# Schottky Barrier Rectifier in DO-214AC/SMA

### **Features**

- Schottky barrier diodes
- Low forward voltage drop
- High Tunction Temperature



### **Mechanical Data**

■ Case: JEDEC DO-214AC(SMA)molded plastic Lead free; RoHS compliant

■ Molding Compound Flammability Rating: UL 94 V-0

■ **Terminals:** High temperature soldering guaranteed: 260 °C/10 sec. at terminals

Absolute Maximum Ratings Ratings at 25 °C, ambient temperature unless otherwise specifi	ed						
Parameter	Symbol	SK12	SK13	SK14	SK16	SK110	Unit
Maximum repetitive peak reverse voltage	$V_{RRM}$	20	30	40	60	100	V
Maximum RMS voltage	$V_{RMS}$	14	21	28	42	70	V
Maximum DC blocking voltage	$V_{DC}$	20	30	40	60	100	V
Maximum average forward rectified current	I <sub>F(AV)</sub>		-	1.0	-	•	Α
Peak forward surge current 8.3 ms single half sine-wave superimposed on rated load	I <sub>FSM</sub>	30		Α			
Operating junction and storage temperature range	$T_J,T_STG$	- 55 to + 150		°C			

Electrical Characteristics								
(T <sub>A</sub> = 25 °C unless otherwise specified	)							
Parameter	Test Conditions	Symbol	SK12	SK13	SK14	SK16	SK110	Unit
Maximum instantaneous forward voltage	I <sub>F</sub> =3A, T <sub>A</sub> =25℃	$V_{F}$		0.55		0.70	0.85	V
Maximum DC reverse current	T <sub>A</sub> =25°C	0.5		0.5				mA
at rated DC blocking voltage	T <sub>A</sub> =125°C	I <sub>R</sub>	50		-	20	ША	
Typical junction capacitance	4.0 V, 1 MHz	$C^{\gamma}$	110 8		0	pF		

Thermal Characteristics							
Parameter Symbo		SK12	SK13	SK14	SK16	SK110	Unit
	$R_{\theta JA}$	90					
Typical thermal resistance <sup>(1)</sup>	$R_{\theta JC}$		°C/W				
	$R_{\theta JI}$	20					

Note1:Thermal resistance from junction to lead,mounted on PCB with 5.0×5.0mm copper pads




## Typical Characteristics (T<sub>amb</sub> = 25 °C unless otherwise specified)


Figure 2. Maximum Non-Repetitive Peak Forward Figure 1. Forward Current Derating Curve **Surge Current Bridge Output Full Wave** Rectified Current, (A) Peak Forward Surge Current 8 SK110 50 Lead temperature ( $^{\circ}$ C) Number of Cycles at 60Hz Figure 3. Typical Instantaneous Forward Figure 4. Typical Reverse Characteristics Characteristics Instantaneous Reverse Current nstantaneous Forward Current (nA) SK12-SK14 SK110 Percent of Rated Peak Reverse Voltage (%) Instantaneous Forward Voltage (V) Figure 5. Typical Junction Capacitance Junction Capacitance (pF) SK12-SK14 Reverse Voltage (V)



## **Package Dimensions**



# **Package Information**



## **Ordering information**

Order code	Package	Packaging option	Base quantity	Packaging specification
SK12 Thur SK110	DO-214AC/SMA	Tape and reel	5000pcs / reel	EIA STD RS-481

## **Revision history**

Date	Revision	Changes
23-May-2012	1.0	Initial release





#### **CAUTION / WARNING**

Information in this document is believed to be accurate and reliable. However, CREATEK does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

Users should independently evaluate the suitability of and test each product selected for their own applications, and CREATEK assumes no liability whatsoever relating to the choice, selection or use of the CREATEK products and services described herein.

CREATEK reserves the right to change or update, without notice, any information contained in this publication; to change, without notice, the design, construction, processing, or specification of any product; and to discontinue or limit production or distribution of any product.

Information in this document supersedes and replaces all information previously supplied.

Products are not designed, authorized or warranted to be suitable for use in medical, military, aircraft, space or life support equipment, nor in applications where failure or malfunction of an CREATEK product can reasonably be expected to result in personal injury, death or severe property or environmental damage. CREATEK accepts no liability for inclusion and/or use of CREATEK products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from national authorities.

Resale of CREATEK products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by CREATEK for the CREATEK product or service described herein and shall not create or extend in any manner whatsoever, any liability of CREATEK.

CREATEK expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. CREATEK only obligations are those in the CREATEK Standard Terms and Conditions of Sale and in no case will CREATEK be liable for any incidental, indirect, or consequential damages arising from the sale, resale, use, or misuse of its products.

Specifications are subject to change without notice

© Copyright 2009,CREATEK Microelectronics

CREATEK® is a registered trademark of CREATEK Microelectronics

All rights reserved